

**DVT
LIGHT**

DMX Charts

PJ-5 RGBW



PJ-5 DMX Default & Strobe

7 Channel Default

CHANNEL	NAME	DMX		DMX PERCENTAGE		DESCRIPTION	INFO
1	Shutter	0	7	0,0%	2,7%	Closed	Snap
		8	15	3,1%	5,9%	Open	Snap
		16	151	6,3%	59,2%	Variable Strobe	Fast → Slow
		152	175	59,6%	68,6%	Pulse - Open	Slow → Fast
		176	199	69,0%	78,0%	Pulse - Close	Slow → Fast
		200	244	78,4%	95,7%	Variable Random Strobe	Fast → Slow
		245	255	96,1%	100,0%	Open	Snap
2	Dimmer	0	255	0,0%	100,0%	0% → 100% Intensity	Fade
3	Active Diffuser	0	255	0,0%	100,0%	0% → 100% Intensity	
4	CTC	0	0	0,0%	0,0%	5600 Kelvin	
		1	4	0,4%	1,6%	Raw	
		5	255	2,0%	100,0%	2000K → 10000K	See CTC chart
5	Red	0	255	0,0%	100,0%	0% → 100% Red	
6	Green	0	255	0,0%	100,0%	0% → 100% Green	
7	Blue	0	255	0,0%	100,0%	0% → 100% Blue	

12 Channel

CHANNEL	NAME	DMX		DMX PERCENTAGE		DESCRIPTION	INFO
1	Shutter	0	7	0,0%	2,7%	Closed	Snap
		8	15	3,1%	5,9%	Open	Snap
		16	151	6,3%	59,2%	Variable Strobe	Fast → Slow
		152	175	59,6%	68,6%	Pulse - Open	Slow → Fast
		176	199	69,0%	78,0%	Pulse - Close	Slow → Fast
		200	244	78,4%	95,7%	Variable Random Strobe	Fast → Slow
		245	255	96,1%	100,0%	Open	Snap
2+3	Dimmer	0	65.535	0,0%	100,0%	0% → 100% Intensity	Fade
4+5	Active Diffuser	0	65.535	0,0%	100,0%	0% → 100% Intensity	
6	CTC	0	0	0,0%	0,0%	5600 Kelvin	
		1	4	0,4%	1,6%	Raw	
		5	255	2,0%	100,0%	2000K → 10000K	See CTC chart
7+8	Red	0	65.535	0,0%	100,0%	0% → 100% Red	
9+10	Green	0	65.535	0,0%	100,0%	0% → 100% Green	
11+12	Blue	0	65.535	0,0%	100,0%	0% → 100% Blue	

22 Channel Strobe

CHANNEL	NAME	DMX	DMX PERCENTAGE		DESCRIPTION	INFO	
1	Shutter	0	7	0,0%	2,7%	Closed	Snap
		8	15	3,1%	5,9%	Open	Snap
		16	151	6,3%	59,2%	Variable Strobe	Fast → Slow
		152	175	59,6%	68,6%	Pulse - Open	Slow → Fast
		176	199	69,0%	78,0%	Pulse - Close	Slow → Fast
		200	244	78,4%	95,7%	Variable Random Strobe	Fast → Slow
		245	255	96,1%	100,0%	Open	Snap
2	Dimmer	0	255	0,0%	100,0%	0% → 100% Intensity	Fade
3	Active Diffuser	0	255	0,0%	100,0%	0% → 100% Intensity	
4	CTC	0	0	0,0%	0,0%	5600 Kelvin	
		1	4	0,4%	1,6%	Raw	
5		5	255	2,0%	100,0%	2000K → 10000K	See CTC chart
6	Red 1	0	255	0,0%	100,0%	0% → 100% Red	
7	Green 1	0	255	0,0%	100,0%	0% → 100% Green	
8	Blue 1	0	255	0,0%	100,0%	0% → 100% Blue	
9	Red 2	0	255	0,0%	100,0%	0% → 100% Red	
10	Green 2	0	255	0,0%	100,0%	0% → 100% Green	
11	Blue 2	0	255	0,0%	100,0%	0% → 100% Blue	
12	Red 3	0	255	0,0%	100,0%	0% → 100% Red	
13	Green 3	0	255	0,0%	100,0%	0% → 100% Green	
14	Blue 3	0	255	0,0%	100,0%	0% → 100% Blue	
15	Red 4	0	255	0,0%	100,0%	0% → 100% Red	
16	Green 4	0	255	0,0%	100,0%	0% → 100% Green	
17	Blue 4	0	255	0,0%	100,0%	0% → 100% Blue	
18	Red 5	0	255	0,0%	100,0%	0% → 100% Red	
19	Green 5	0	255	0,0%	100,0%	0% → 100% Green	
20	Blue 5	0	255	0,0%	100,0%	0% → 100% Blue	
21	Red 6	0	255	0,0%	100,0%	0% → 100% Red	
22	Green 6	0	255	0,0%	100,0%	0% → 100% Green	
	Blue 6	0	255	0,0%	100,0%	0% → 100% Blue	

DVT Light Holding ApS

Ribevej 13b

8940 Randers SV

Denmark

+45 70 270 730

sales@dvtlight.com

www.dvtlight.com

The logo consists of the words "DVT" and "LIGHT" stacked vertically in a bold, white, sans-serif font, centered within a black rounded square. A thick black horizontal line extends from the left edge of the page to the right edge of the logo square.

**DVT
LIGHT**

